

# ToolBox v4

## Installation Guide

2025 December



Chyron • ToolBox Installation Guide • v4.0.1 • December 2025 • This document is distributed by Chyron in online (electronic) form only, and is not available for purchase in printed form.

This document is protected under copyright law. An authorized licensee of Chyron ToolBox may reproduce this publication for the licensee's own use in learning how to use the software. This document may not be reproduced or distributed, in whole or in part, for commercial purposes, such as selling copies of this document or providing support or educational services to others.

Product specifications are subject to change without notice and this document does not represent a commitment or guarantee on the part of Chyron and associated parties. This product is subject to the terms and conditions of Chyron's software license agreement. The product may only be used in accordance with the license agreement.

Any third-party software mentioned, described or referenced in this guide is the property of its respective owner. Instructions and descriptions of third-party software are for informational purposes only, as related to Chyron products and does not imply ownership, authority or guarantee of any kind by Chyron and associated parties.

This document is supplied as a guide for Chyron ToolBox. Reasonable care has been taken in preparing the information it contains. However, this document may contain omissions, technical inaccuracies, or typographical errors. Chyron and associated companies do not accept responsibility of any kind for customers' losses due to the use of this document. Product specifications are subject to change without notice.

Copyright © 2025 Chyron, ChyronHego Corp. and its licensors. All rights reserved.

## Table of Contents

01: Requirements.....	4
02: Architecture.....	5
03: SDI Card Installation.....	6
04: Toolbox Software Installation.....	7

# 01: Requirements


Before you begin, please check the system requirements:

- Latest NVIDIA Driver for the graphics card.
- VLC Media Player installed (version 3.0.17 can be downloaded from <http://download.videolan.org/pub/videolan/vlc/>).


Hardware requirements are listed under [TOOLBOX 4 > RELEASE NOTES > SYSTEM REQUIREMENTS](#)

## 02: Architecture

The following figure depicts the possible ways of how you can connect the Toolbox workstation. The top one represents a configuration where audio and video is handled separately and the bottom one represents the embedded configuration.



The following figure depicts the architecture when the optional video chat return signal feature is available.



## 03: SDI Card Installation

Turn off the PC and place the SDI card in a PCI Express x16 (recommended) or x8 slot.

Turn on the PC. Windows will detect the new hardware and start the “Add New Hardware Wizard” but needs your assistance to install the drivers for the SDI card.

Please make sure to install SDI Card drivers before installing the Toolbox. You will find the required drivers for BlackMagic Decklink and Deltacast together with Toolbox installer download. Click Install when you are asked “would you like to install this device software?”. Click Finish to conclude the driver installation sequence. When you are prompted to restart your computer, select later and continue with the next step.

# 04: Toolbox Software Installation

The Toolbox download contains the following:

- Toolbox Installer
- Toolbox User and Installation Guide
- Blackmagic and Deltacast Drivers
- VLC Installer

In case of an update: before installing the new version of the software, first uninstall the previous version of Toolbox via the Microsoft Windows Control Panel (Programs and Features).

1. Double-click the Toolbox installer and follow the on-screen instructions.
2. When prompted with a dialog box about Windows Logo testing, click Continue anyway.
3. Click Install when you are asked “Would you like to install this device software?”.
4. Click Finish to conclude the driver installation sequence. When you are prompted to restart your computer, select later and continue with the next step.

**For installation from command line, you can use the following command:**

ChyronToolbox\_4.0.1.exe

/SILENT, /VERYSILENT

Instructs Setup to be silent or very silent. When Setup is silent the wizard and the background window are not displayed but the installation progress window is. When a setup is very silent this installation progress window is not displayed.

## **ABOUT US**

Chyron is ushering in the next generation of storytelling in the digital age. Founded in 1966, the company pioneered broadcast titling and graphics systems. With a strong foundation built on over 50 years of innovation and efficiency, the name Chyron is synonymous with broadcast graphics. Chyron continues that legacy as a global leader focused on customer-centric broadcast solutions. Today, the company offers production professionals the industry's most comprehensive software portfolio for designing, sharing, and playing live graphics to air with ease. Chyron products are increasingly deployed to empower OTA & OTT workflows and deliver richer, more immersive experiences for audiences and sports fans in the arena, at home, or on the go.

## **CONTACT SALES**

EMEA • North America • Latin America • Asia/Pacific  
+1.631.845.2000 • [sales@chyron.com](mailto:sales@chyron.com)

